

ISC-HH Intelligent Controller

Basketball Shot Clock – Dual Reset



ISC-HH Operation

The ISC-HH is an independent controller, it is not tied into any OES controller or system- it is a standalone system. The shot clocks are not linked to any function of the game time and run independently.

The ISC-HH is battery operated. A battery should provide several games of operation. When the shot clock displays start ignoring ISC-HH commands, it is time to replace the battery. If the ISC-HH is not used for several days, removing the battery will extend its life.

Shot Clock Displays – ON/OFF

- When the displays are off, press any key to turn them on.
- To turn the displays off, press and hold the SET STANDARD key.

Shot Clock Displays – MODES

Because the ISC-HH does not have a display, the shot clock displays will offer the operator visuals to ensure proper operation. The display has two digits and two indicator lights to the right of the digits. When the displays are on, the indicator lights will illuminate as follows:

- LIGHTS BLANK – Game mode, clock stopped.
- LOWER LIGHT SOLID – Game Mode, Clock Running.
- UPPER LIGHT FLASHING- Set Mode, Setting Standard Time A.
- BOTH LIGHTS FLASHING- Set Mode, Setting Standard Time B.

Shot Clock Operation

- To Start/stop the shot clock timer, press the START/STOP key.
- To reset the shot clock time to the standard time, either press the RESET key.
- To keep the shot clock time at a standard time, either:

- Stop the time as described above
- Press and hold the appropriate RESET key

-To adjust Standard Time:

- Stop the time as described above
- Press the SET STANDARD key.
- On the STANDARD A time: Press + or – to get to desired time
- Press the SET STANDARD key.
- On the STANDARD B time: Press + or – to get to desired time
- Press the SET STANDARD key.